

TOPICS IN NONHAMILTONIAN (MAGNETIC-TYPE) INTERACTION OF CLASSICAL HAMILTONIAN DYNAMIC SYSTEMS

DENIS JURIEV¹

ABSTRACT. A convenient algebraic structure to describe some forms of dynamics of two hamiltonian systems with nonpotential (magnetic-type) interaction is considered. An algebraic mechanism of generation of such dynamics is explored on simple "toy" examples and models. Nonpotential chains and their continuum limits are also considered. Examples of hybrid couplings with both potential and nonpotential (magnetic-type) interactions are discussed.

I. INTRODUCTION

The evolution of hamiltonian systems (defined by Poisson brackets and hamiltonians) attracts a lot of attention (see f.e. [1]). Many of such systems are associated with Lie algebras, in this case Poisson brackets (the so-called Lie-Berezin brackets) have a linear form and are restored from the commutator in the Lie algebra [2] (it should be marked that nonlinear Poisson brackets are also of interest [3]). The introducing of external fields (which interact with the system nonpotentially, in general) may be accounted by a transformation of commutator Lie algebras into the so-called isocommutator Lie algebras (their Q -operator deformations). It means that if a Lie algebra is realized by operators with an ordinary commutator $[X, Y] = XY - YX$, the corresponding isocommutator Lie algebra (its Q -operator deformation) is realised by operators with the so-called isocommutator $[X, Y]_Q = XQY - YQX$, where an additional fixed operator Q decodes an information on the external field (see f.e. [4]). If the external field possesses a symmetry governed by the Lie algebra $\mathfrak{g}$, then it is rather convenient to describe the systems by Lie $\mathfrak{g}$ -bunches [5]. This is a standard situation for magnetic-type external fields (see f.e. [6]). By use of Lie $\mathfrak{g}$ -bunches one may construct various hamiltonian systems nonpotentially controlled by external fields, which dynamics maybe also hamiltonian, in particular. Such picture is rather realistic if one supposes that a counteraction of the system on the external fields maybe neglected. Nevertheless, it is not so in many important cases. Therefore, it is interesting to consider a dynamics of two hamiltonian systems, which interact with each other noncanonically (nonpotentially). For example, a system of two charged spinning particles with nonpotential magnetic-type

¹A preliminary electronic version of this manuscript is located in the Texas e-print archive on mathematical physics and has a number "mp-arc/94-136" (May, 1994).

interaction may be considered as an example. A convenient algebraic structure to describe some forms of such dynamics seems to be of the following definition (see, however, [7] for more general one).

Definition 1. The pair (V_1, V_2) of linear spaces is called *an isotopic pair* iff there are defined two mappings $m_1 : V_2 \otimes \bigwedge^2 V_1 \mapsto V_1$ and $m_2 : V_1 \otimes \bigwedge^2 V_2 \mapsto V_2$ such that the mappings $(X, Y) \mapsto [X, Y]_A = m_1(A, X, Y)$ ($X, Y \in V_1, A \in V_2$) and $(A, B) \mapsto [A, B]_X = m_2(X, A, B)$ ($A, B \in V_2, X \in V_1$) obey the Jacobi identity for all values of a subscript parameter (such operations will be called *isocommutators* and the subscript parameters will be called *isotopic elements*) and are compatible to each other, i.e. the identities

$$[X, Y]_{[A, B]_Z} = \frac{1}{2}([X, Z]_A, Y)_B + [[X, Y]_A, Z]_B + [[Z, Y]_A, X]_B - \\ [[X, Z]_B, Y]_A - [[X, Y]_B, Z]_A - [[Z, Y]_B, X]_A$$

and

$$[A, B]_{[X, Y]_C} = \frac{1}{2}([A, C]_X, B)_Y + [[A, B]_X, C]_Y + [[C, B]_X, A]_Y - \\ [[A, C]_Y, B]_X - [[A, B]_Y, C]_X - [[C, B]_Y, A]_X$$

$(X, Y, Z \in V_1, A, B, C \in V_2)$ hold.

This definition is a result of an axiomatization of the following construction. Let's consider an associative algebra $\mathcal{A}$ (f.e. any matrix algebra) and two linear subspaces V_1 and V_2 in it such that V_1 is closed under the isocommutators $(X, Y) \mapsto [X, Y]_A = XAY - YAX$ with isotopic elements A from V_2 , whereas V_2 is closed under the isocommutators $(A, B) \mapsto [A, B]_X = AXB - BXA$ with isotopic elements X from V_1 . If a family (linear space) V_1 of operators forms an isocommutator algebra with a family (linear space) V_2 of admissible isotopic elements then (V_1, V_2) is an isotopic pair via the so-called "isotopic duality" [5] (which maybe regarded as a certain "algebraic manifestation" of the Third Law of Classical Dynamics).

It should be mentioned that the isocommutators define families of Poisson brackets $\{\cdot, \cdot\}_A$ and $\{\cdot, \cdot\}_X$ ($A \in V_2, X \in V_1$) in the spaces $S(V_1)$ and $S(V_2)$, respectively.

Definition 2A. Let's consider two elements $\mathcal{H}_1$ and $\mathcal{H}_2$ (hamiltonians) in $S(V_1)$ and $S(V_2)$, respectively. The equations

$$\dot{X}_t = \{\mathcal{H}_1, X_t\}_{A_t}, \quad \dot{A}_t = \{\mathcal{H}_2, A_t\}_{X_t},$$

where $X_t \in V_1$ and $A_t \in V_2$ will be called *the (nonlinear) dynamical equations associated with the isotopic pair (V_1, V_2) and hamiltonians $\mathcal{H}_1$ and $\mathcal{H}_2$* .

Definition 2B. Let's consider two elements $\Omega^\pm$ in V_1 and V_2 , respectively. The equations

$$\dot{X}_t = [\Omega^+, X_t]_{A_t}, \quad \dot{A}_t = [\Omega^-, A_t]_{X_t},$$

where $X_t \in V_1$ and $A_t \in V_2$ will be called *the (nonlinear) dynamical equations (Euler formulas) associated with the isotopic pair (V_1, V_2) and elements $\Omega^\pm$* .

Let's consider several simple but crucial examples now. We shall treat the subject purely mathematically and shall not specify its concrete physical implications of a possible interest in details.

II. NONCANONICALLY COUPLED ROTATORS AND EULER-ARNOLD TOPS

2.1. Nonlinear integrable dynamics of noncanonically coupled rotators. Let's consider the Lie $\mathfrak{sl}(2, \mathbb{C})$ -bunch in π_1 (the adjoint representation of $\mathfrak{sl}(2, \mathbb{C})$)⁵. It is defined by the next formulas

$$(1) \quad \begin{aligned} [m_{-1}, m_0]_{l_0} &= m_{-1} & [m_{-1}, m_0]_{l_{-1}} &= 0 & [m_{-1}, m_0]_{l_1} &= 2m_0 \\ [m_1, m_{-1}]_{l_0} &= 0 & [m_1, m_{-1}]_{l_{-1}} &= 2m_{-1} & [m_1, m_{-1}]_{l_1} &= -2m_1 \\ [m_1, m_0]_{l_0} &= m_1 & [m_1, m_0]_{l_{-1}} &= 2m_0 & [m_1, m_0]_{l_1} &= 0 \end{aligned}$$

where l_i ($i = -1, 0, 1$) are generators of $\mathfrak{sl}(2, \mathbb{C})$ ($[l_i, l_j] = (i - j)l_{i+j}$), m_i ($i = -1, 0, 1$) form a basis in π_1 ($l_i(m_j) = (i - j)m_{i+j}$).

As it was marked in [5] the operators l_i form an isocommutator Lie algebra with respect to isotopic elements from π_1 via the "isotopic duality", namely

$$(2) \quad \begin{aligned} [l_{-1}, l_0]_{m_0} &= -l_{-1} & [l_{-1}, l_0]_{m_{-1}} &= 0 & [l_{-1}, l_0]_{m_1} &= -2l_0 \\ [l_1, l_{-1}]_{m_0} &= 0 & [l_1, l_{-1}]_{m_{-1}} &= -2l_{-1} & [l_1, l_{-1}]_{m_1} &= 2l_1 \\ [l_1, l_0]_{m_0} &= -l_1 & [l_1, l_0]_{m_{-1}} &= -2l_0 & [l_1, l_0]_{m_1} &= 0 \end{aligned}$$

It can be easily verified that isocommutators (1) and (2) define a structure of an isotopic pair in $\pi_1 \oplus \pi_1$. Mark that all isocommutators are r -matrix ones, i.e. may be constructed from a standard Lie bracket in 3-dimensional Lie algebra $\mathfrak{sl}(2, \mathbb{R})$ by use of classical r -matrices (see [8]).

Let's denote the first summand π_1 by π_1^+ and the second summand by π_1^- . Let's also consider two fixed elements $\Omega^\pm$ in $\pi_1^\pm$, respectively ($\Omega^+ = \Omega_{-1}^+ m_{-1} + \Omega_0^+ m_0 + \Omega_1^+ m_1$, $\Omega^- = \Omega_{-1}^- l_{-1} + \Omega_0^- l_0 + \Omega_1^- l_1$), and two variables A and B from π_1^+ and π_1^- ($A = A_{-1} m_{-1} + A_0 m_0 + A_1 m_1$ and $B = B_{-1} l_{-1} + B_0 l_0 + B_1 l_1$). The dynamical equations (Euler formulas) defined by $\Omega^\pm$ will have the form

$$\begin{cases} \dot{A}_{-1} = \Omega_{-1}^+(A_0 B_0 - 2A_1 B_{-1}) - \Omega_0^+ A_{-1} B_0 + 2\Omega_1^+ A_{-1} B_{-1} \\ \dot{A}_0 = 2\Omega_{-1}^+ A_0 B_1 + 2\Omega_0^+ (A_1 B_{-1} - A_{-1} B_1) + 2\Omega_1^+ A_0 B_{-1} \\ \dot{A}_1 = 2\Omega_{-1}^+ A_1 B_1 - \Omega_0^+ A_1 B_0 + \Omega_1^+ (A_0 B_0 - 2A_{-1} B_1) \end{cases}$$

$$\begin{cases} \dot{B}_{-1} = -\Omega_{-1}^-(B_0 A_0 - 2B_1 A_{-1}) + \Omega_0^- B_{-1} A_0 - 2\Omega_1^- B_{-1} A_{-1} \\ \dot{B}_0 = -2\Omega_{-1}^- B_0 A_1 - 2\Omega_0^- (B_1 A_{-1} - B_{-1} A_1) - 2\Omega_1^- B_0 A_{-1} \\ \dot{B}_1 = -2\Omega_{-1}^- B_1 A_1 + \Omega_0^- B_1 A_0 - \Omega_1^- (B_0 A_0 - 2B_{-1} A_1) \end{cases}$$

It is rather convenient to consider the compact real form of the isotopic pair (π_1^+, π_1^-) . Let's denote

$$\begin{aligned} l_x &= \frac{i}{2}(l_1 - l_{-1}), & l_y &= \frac{1}{2}(l_1 + l_{-1}), & l_z &= il_0 \\ m_x &= \frac{i}{2}(m_1 - m_{-1}), & m_y &= \frac{1}{2}(m_1 + m_{-1}), & m_z &= im_0. \end{aligned}$$

The dynamical equation maybe rewritten as

$$\begin{cases} \dot{A}_x = -\Omega_x^+(A_y B_y + A_z B_z) + \Omega_y^+ A_x B_y + \Omega_z^+ A_x B_z \\ \dot{A}_y = -\Omega_y^+(A_x B_x + A_z B_z) + \Omega_x^+ A_y B_x + \Omega_z^+ A_y B_z \\ \dot{A}_z = -\Omega_z^+(A_x B_x + A_y B_y) + \Omega_x^+ A_z B_x + \Omega_y^+ A_z B_y \end{cases}$$

$$\begin{cases} \dot{B}_x = -\Omega_x^-(B_y A_y + B_z A_z) + \Omega_y^- B_x A_y + \Omega_z^- B_x A_z \\ \dot{B}_y = -\Omega_y^-(B_x A_x + B_z A_z) + \Omega_x^- B_y A_x + \Omega_z^- B_y A_z \\ \dot{B}_z = -\Omega_z^-(B_x A_x + B_y A_y) + \Omega_x^- B_z A_x + \Omega_y^- B_z A_y \end{cases}$$

after the change $\Omega^- \rightarrow -\Omega^-$. They maybe also written in a more compact form

$$\begin{cases} \dot{A} = -\langle A, B \rangle \Omega^+ + \langle \Omega^+, B \rangle A \\ \dot{B} = -\langle A, B \rangle \Omega^- + \langle \Omega^-, A \rangle B \end{cases}$$

here brackets $\langle \cdot, \cdot \rangle$ denote $\mathfrak{su}(2)$ -invariant inner products in $\pi_1^\pm$. Such nonlinear dynamics maybe interpreted as one for the noncanonically coupled rotators. It possesses two trivial integrals of motion $K = \langle A, B \rangle$ and $L = \langle A, \Omega^- \rangle - \langle B, \Omega^+ \rangle$.

Let's denote $\langle \Omega^+, B \rangle + \frac{1}{2}L = \langle \Omega^-, A \rangle - \frac{1}{2}L$ by y . Then

$$\begin{cases} \dot{A} = -K\Omega^+ + (y - \frac{1}{2}L)A \\ \dot{B} = -K\Omega^- + (y + \frac{1}{2}L)B \end{cases}$$

whereas

$$\dot{y} = y^2 - (\frac{1}{4}L^2 + K\beta),$$

$\beta = \langle \Omega^+, \Omega^- \rangle$, so the dynamical equations (Euler formulas) are integrable in elementary functions.

2.2. Nonlinear integrable dynamics of noncanonically coupled Euler–Arnold tops. Noncanonically coupled Euler–Arnold tops are realized by means of the same isotopic pair as noncanonically coupled rotators but with quadratic hamiltonians $\mathcal{H}_1 = \langle A, T_1 A \rangle$ and $\mathcal{H}_2 = \langle B, T_2 B \rangle$ ($T_i = T_i^*$). The corresponding dynamical equations maybe written as

$$\begin{cases} \dot{A} = -\langle T_1 A, A \rangle B + \langle T_1 A, B \rangle A \\ \dot{B} = -\langle T_2 B, A \rangle B + \langle T_2 B, B \rangle A \end{cases}$$

Such system admits integrals of motion $K_A = \langle T A, A \rangle$, $K_B = \langle T B, B \rangle$. If $T_1 = T_2 = T$ then $L = \langle T A, B \rangle = \langle T B, A \rangle$ is also an integral; the equations maybe rewritten as

$$\begin{cases} \dot{A} = L A - K_A B \\ \dot{B} = K_B A - L B \end{cases}$$

and are easily integrated.

It is rather interesting to obtain solutions of dynamical equations with $T_1 \neq T_2$ by use of some sort of "dynamical dressing transformations" (cf. [9]).

III. NONCANONICALLY COUPLED OSCILLATORS AND THEIR CHAINS

3.1. Nonlinear integrable dynamics of noncanonically coupled oscillators. Let's consider a standard representation of the Heisenberg algebra with three generators p , q and r ($[p, q] = r$, $[p, r] = [q, r] = 0$) by 3×3 matrices:

$$p = \begin{pmatrix} 0 & 1 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{pmatrix}, \quad q = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 1 \\ 0 & 0 & 0 \end{pmatrix}, \quad r = \begin{pmatrix} 0 & 0 & 1 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{pmatrix}.$$

The linear space of admissible isotopic elements is generated by three elements a , b and c , which are represented by matrices

$$a = \begin{pmatrix} 0 & 0 & 0 \\ 1 & 0 & 0 \\ 0 & 0 & 0 \end{pmatrix}, \quad b = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 1 & 0 \end{pmatrix}, \quad c = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 0 \end{pmatrix}.$$

The isocommutators have the form

$$\begin{aligned} [p, q]_a &= 0 & [p, q]_b &= 0 & [p, q]_c &= r \\ [p, r]_a &= r & [p, r]_b &= 0 & [p, r]_c &= 0 \\ [q, r]_a &= 0 & [q, r]_b &= -r & [q, r]_c &= 0 \end{aligned}$$

The elements a , b and c are closed themselves under isocommutators with isotopic elements p , q and r via the "isotopic duality":

$$\begin{aligned} [a, b]_p &= 0 & [a, b]_q &= 0 & [a, b]_r &= c \\ [a, c]_p &= c & [a, c]_q &= 0 & [b, c]_r &= 0 \\ [b, c]_p &= 0 & [b, c]_q &= -c & [a, c]_r &= 0 \end{aligned}$$

The linear spaces generated by p , q , r and a , b , c form an isotopic pair. One may associate noncanonically coupled oscillators with it; namely, let's consider p , q , r and a , b , c as linear functionals (we shall denote them by capitals) on dual spaces; hamiltonians $\mathcal{H}_1$ and $\mathcal{H}_2$ will be of the form $\mathcal{H}_1 = P^2 + Q^2$ and $\mathcal{H}_2 = A^2 + B^2$, the dynamical equations will be written as

$$\begin{cases} \dot{Q} = 2RPC \\ \dot{P} = -2RQC \\ \dot{R} = 2PRA - 2QRB \end{cases} \quad \begin{cases} \dot{A} = -2CBR \\ \dot{B} = 2CAR \\ \dot{C} = 2ACP - 2BCQ \end{cases}$$

It should be marked that hamiltonians are integrals of motion here, also three integrals maybe written: $\mathcal{M} = AQ - BP$, $\mathcal{N} = BQ + AP$ and $\mathcal{L} = CR - BP - AQ = CR - 2BP - \mathcal{M} = CR - 2AQ + \mathcal{M}$. The presence of five integrals essentially simplifies a picture, so an integration of the system of two noncanonically coupled oscillators becomes an easy but interesting exercise. Let's perform it. Put $\mathcal{H}_1 = h_1^2$, $\mathcal{H}_2^2 = h_2^2$, $P = h_1 \cos \varphi$, $Q = h_1 \sin \varphi$, $A = h_2 \cos \psi$, $B = h_2 \sin \psi$, then the condition $\dot{\mathcal{M}} = \dot{\mathcal{N}} = 0$ gives $\cos(\varphi - \psi) = -\frac{\mathcal{N}}{h_1 h_2}$, $\sin(\varphi - \psi) = \frac{\mathcal{M}}{h_1 h_2}$, so $\vartheta := \psi - \varphi = \arctan(\frac{\mathcal{M}}{\mathcal{N}})$. Also $\dot{\varphi} = \dot{\psi} = 2CR$, $\dot{R} = 2Rh_1 h_2 \cos(\varphi + \psi)$, $\dot{C} = 2Ch_1 h_2 \cos(\varphi + \psi)$, hence $C = \varkappa R$ and $\dot{\varphi} = 2\varkappa R^2$, $\dot{R} = 2h_1 h_2 R \cos(2\varphi + \vartheta)$. Let's consider R as a function of φ then $RR'_\varphi = h_1 h_2 \cos(2\varphi + \vartheta)$ and $R = \sqrt{\frac{\mathcal{L}}{\varkappa} + \frac{h_1 h_2}{\varkappa} \sin(2\varphi + \vartheta)}$ (to receive this fact one may also use a conservation law $\dot{\mathcal{L}} = 0$). It should be marked that the plane curve, which is defined by the equation $R = R(\varphi)$ in polar coordinates, is the Booth lemniscate. Substituting the resulted expression for $R = R(\varphi)$ into the formula for $\dot{\varphi}$ one obtains that $\dot{\varphi} = 2\mathcal{L} + 2h_1 h_2 \sin(2\varphi + \vartheta)$.

3.2. Dynamics of periodic and nonperiodic chains of noncanonically coupled oscillators. The dynamical equations for two noncanonically coupled oscillators are immediately generalized on (periodic or infinite nonperiodic) chains

of them, namely

$$\begin{cases} \dot{Q}_i = R_i P_i (R_{i-1} + R_{i+1}) \\ \dot{P}_i = -R_i Q_i (R_{i-1} + R_{i+1}) \\ \dot{R}_i = R_i P_i (P_{i-1} + P_{i+1}) - R_i Q_i (Q_{i-1} + Q_{i+1}) \end{cases}$$

The hamiltonians $\mathcal{H}_i = P_i^2 + Q_i^2$ are certainly integrals of motion. Put $\mathcal{H}_i = h_i^2$, $P_i = h_i \cos \varphi_i$, $Q_i = h_i \sin \varphi_i$, then $\dot{\varphi}_i = R_i (R_{i-1} + R_{i+1})$, $\dot{R}_i = R_i h_i (h_{i-1} \cos(\varphi_i + \varphi_{i-1}) + h_{i+1} \cos(\varphi_i + \varphi_{i+1}))$.

Let's introduce new "coupled" variables $\psi_i = \varphi_i + \varphi_{i+1}$ and $S_i = R_i R_{i+1}$ as well as $H_i = h_i h_{i+1}$. The dynamical equations are rewritten as follows

$$\begin{cases} \dot{\psi}_i = S_{i-1} + 2S_i + S_{i+1} \\ \dot{S}_i = S_i (H_{i-1} \cos \psi_{i-1} + 2H_i \cos \psi_i + H_{i+1} \cos \psi_{i+1}) \end{cases}$$

Let's put $T_i = H_i e^{\sqrt{-1}\psi_i}$ now, then

$$\begin{cases} \dot{S}_i = \text{Re}(T_{i-1} + 2T_i + T_{i+1})S_i \\ \dot{T}_i = \sqrt{-1}(S_{i-1} + 2S_i + S_{i+1})T_i \end{cases}$$

3.3. A continuum limit of the noncanonically coupled oscillator chain. One may consider noncanonically coupled oscillator chain with changed signs, i.e.

$$\begin{cases} \dot{Q}_i = R_i P_i (R_{i+1} - R_{i-1}) \\ \dot{P}_i = -R_i Q_i (R_{i+1} - R_{i-1}) \\ \dot{R}_i = R_i P_i (P_{i+1} - P_{i-1}) - R_i Q_i (Q_{i+1} - Q_{i-1}) \end{cases}$$

Such chain admits a natural continuum (field) limit

$$\begin{cases} \dot{q} = p r r'_x \\ \dot{p} = -q r r'_x \\ \dot{r} = r p p'_x - r q q'_x \end{cases}$$

$q = q(t, x)$, $p = p(t, x)$, $r = r(t, x)$. The function $h^2 = p^2 + q^2$ is an integral of motion, so it is convenient to put $p = h \cos \varphi$, $q = h \sin \varphi$. Then

$$\begin{cases} \dot{\phi} = r r'_x \\ \dot{r} = -r h^2 \sin 2\varphi \varphi'_x \end{cases}$$

Let's put $s = r^2$, $t = h^2 e^{2\sqrt{-1}\varphi}$, then

$$\begin{cases} \dot{s} = -\text{Re}(t'_x) s \\ \dot{t} = \sqrt{-1} s'_x t \end{cases}$$

IV. OTHER EXAMPLES

4.1. Dynamic system connected with the isotopic pair of 3×3 symmetric and skew-symmetric matrices. One of the most interesting examples of isotopic pairs is related to $n \times n$ symmetric and skew-symmetric matrices. Let's consider the simplest case $n = 3$. It is rather convenient to introduce the following bases:

$$l_z = \begin{pmatrix} 0 & 1 & 0 \\ -1 & 0 & 0 \\ 0 & 0 & 0 \end{pmatrix}, \quad l_x = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 1 \\ 0 & -1 & 0 \end{pmatrix}, \quad l_y = \begin{pmatrix} 0 & 0 & 1 \\ 0 & 0 & 0 \\ -1 & 0 & 0 \end{pmatrix}$$

and

$$m_{xy} = \begin{pmatrix} 0 & 1 & 0 \\ 1 & 0 & 0 \\ 0 & 0 & 0 \end{pmatrix}, \quad m_{yz} = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 1 \\ 0 & 1 & 0 \end{pmatrix}, \quad m_{xz} = \begin{pmatrix} 0 & 0 & 1 \\ 0 & 0 & 0 \\ 1 & 0 & 0 \end{pmatrix},$$

$$m_{xx} = \begin{pmatrix} 2 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{pmatrix}, \quad m_{yy} = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 2 & 0 \\ 0 & 0 & 0 \end{pmatrix}, \quad m_{zz} = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 2 \end{pmatrix}.$$

Elements l_a form a basis in the space of skew-symmetric matrices, whereas w_{ab} form a basis in the space of symmetric matrices. The isocommutators have the form

$$\begin{aligned} [m_{ab}, m_{cd}]l_e &= \epsilon_{ace}m_{bd} + \epsilon_{ade}m_{bc} + \epsilon_{bce}m_{ad} + \epsilon_{bde}m_{ac}, \\ [l_a, l_b]m_{cd} &= \epsilon_{abc}l_d + \epsilon_{abd}l_c, \end{aligned}$$

here ϵ_{abc} is a totally antisymmetric tensor.

Let's fix a skew-symmetric matrix Ω^- and a symmetric matrix Ω^+ . If the linear functionals defined by l_a and m_{ab} in the dual spaces are denoted by capitals L_a and M_{ab} , respectively, then the dynamical equations (Euler formulas) will have the form

$$\begin{cases} \dot{L}_a = \epsilon_{bcd}\Omega_b^- L_c M_{ad} \\ \dot{M}_{ab} = \epsilon_{cde}\Omega_{ac}^+ M_{bd} L_e + \epsilon_{cde}\Omega_{bc}^+ M_{ad} L_e \end{cases}$$

Unfortunately, I do not know whether this system is integrable.

4.2. The hybrid coupling: "elastoplastic" spring. It is rather interesting to consider the case then two hamiltainian systems are coupled by interaction terms in a hamiltonian and simultaneously noncanonically. Below we shall consider an "elastoplastic" string, which is a hybrid of the ordinary "elastic" spring with noncanonically coupled oscillators.

The isotopic pair is the same as for noncanonically coupled oscillators but the hamiltonian is of the form $\mathcal{H} = \mathcal{H}_1 + \mathcal{H}_2 - 2QB - 2PA$; the dynamical equations have the form

$$\begin{cases} \dot{Q} = 2RC(P - A) \\ \dot{P} = -2RC(Q - B) \\ \dot{R} = -2(P - A)^2 R + 2(Q - B)^2 R \end{cases} \quad \begin{cases} \dot{A} = 2RC(Q - B) \\ \dot{B} = -2RC(P - A) \\ \dot{C} = -2(P - A)^2 C + 2(Q - B)^2 C \end{cases}$$

Let's denote $D = P - A$, $G = Q - B$, then $\mathcal{J}^2 = D^2 + G^2$ is an integral of motion so it is convenient to put $D = \mathcal{J} \sin \varphi$, $G = \mathcal{J} \cos \varphi$. Moreover, $C = \lambda R$ and $\dot{R} = 2\mathcal{J}^2 R^2 \cos 2\varphi$, whereas $\dot{\varphi} = -4\lambda R^2$. Hence, $-2\lambda R R'_\varphi = \mathcal{J}^2 \cos 2\varphi$ and $R = \sqrt{\frac{\mathcal{L}}{\lambda} - \frac{1}{2\lambda} \mathcal{J}^2 \sin 2\varphi}$ (and the corresponding plane curve is the Booth lemniscate again), whereas $\dot{\varphi} = -4\mathcal{L} + 2\mathcal{J}^2 \sin 2\varphi$.

4.3. "Elastoplastic" spring with general interaction potential. The described picture is straightforwardly generalized on arbitrary interaction potentials. Namely, let's consider the hamiltonian of the form $\mathcal{H} = (P - A)^2 + V(Q - B)$, where V is an interaction potential. The dynamical equations are written in the form

$$\begin{cases} \dot{Q} = 2RC(P - A) \\ \dot{P} = -RCV'(Q - B) \\ \dot{R} = -2(P - A)^2 R + (Q - B)V'(Q - B)R \end{cases}$$

$$\begin{cases} \dot{A} = RCV'(Q - B) \\ \dot{B} = -2RC(P - A) \\ \dot{C} = -2(P - A)^2 C + (Q - B)V'(Q - B)C \end{cases}$$

Let's denote $D = P - A$, $G = Q - B$; $\mathcal{J}^2 = D^2 + V(G)$ is an integral of motion so it is convenient to put $D = \mathcal{J} \sin \varphi$, $G = V^{-1}(\mathcal{J}^2 \cos^2 \varphi)$. Moreover $C = \lambda R$ and $\dot{R} = [-2\mathcal{J}^2 \sin^2 \varphi + V^{-1}(\mathcal{J}^2 \cos^2 \varphi)V'(V^{-1}(\mathcal{J}^2 \cos^2 \varphi))] R$, whereas $\dot{\varphi} = -\frac{2\lambda R^2}{\mathcal{J} \cos \varphi} \times V'(V^{-1}(\mathcal{J}^2 \cos^2 \varphi))$. Hence $-2\lambda R R'_\varphi V'(V^{-1}(\mathcal{J}^2 \cos^2 \varphi)) = \mathcal{J} \cos \varphi [-2\mathcal{J}^2 \sin^2 \varphi + V^{-1}(\mathcal{J}^2 \cos^2 \varphi)V'(V^{-1}(\mathcal{J}^2 \cos^2 \varphi))]$ and

$$R = \sqrt{\frac{1}{\lambda} \int \mathcal{J} \cos \varphi \frac{2\mathcal{J}^2 \sin^2 \varphi - V^{-1}(\mathcal{J}^2 \cos^2 \varphi)V'(V^{-1}(\mathcal{J}^2 \cos^2 \varphi))}{V'(V^{-1}(\mathcal{J}^2 \cos^2 \varphi))} d\varphi},$$

whereas

$$\dot{\varphi} = \frac{2}{\cos \varphi} \int \cos \varphi \left[V^{-1}(\mathcal{J}^2 \cos^2 \varphi) - \frac{2\mathcal{J}^2 \sin^2 \varphi}{V'(V^{-1}(\mathcal{J}^2 \cos^2 \varphi))} \right] d\varphi.$$

V. CONCLUSIONS

Thus, a certain convenient algebraic structure (a structure of *isotopic pair*) to describe some forms of classical dynamics of two hamiltonian systems with non-potential (magnetic-type) interaction was considered. An algebraic mechanism of generation of such dynamics was explored on simple "toy" examples (coupled rotators, tops and oscillators). It is analogous to well-known one for hamiltonian systems constructed from Lie algebras (see f.e. [10]). The nonpotential chains and their continuum (field) limits were also considered. Examples of hybrid couplings with both potential and nonpotential terms were discussed.

REFERENCES

- [1] Arnold V.I., *Mathematical methods of classical mechanics*, Springer-Verlag, 1980; Dubrovin B.A., Novikov S.P., Fomenko A.T., *Modern geometry – methods and applications*, Springer-Verlag, 1988; Fomenko A.T., *Symplectic geometry. Methods and applications*, Gordon & Beach, 1988; Arnold V.I., Kozlov V.V., Neustadt A.I., Current Problems of Math., Fundamental Directions. Vol.3. Moscow, VINITI, 1985, pp.5-303 [in Russian].
- [2] Kirillov A.A., *Elements of the theory of representations*, Springer-Verlag, 1976; Perelomov A.M., *Integrable systems of classical mechanics and Lie algebras*, Birkhauser-Verlag, 1990.
- [3] Karasev M.V., Maslov V.P., *Nonlinear Poisson brackets: geometry and quantization*, Amer. Math. Soc., Providence, RI, 1993.
- [4] Santilli R.M., *Foundations of theoretical mechanics. II. Birkhoffian generalization of Hamiltonian mechanics*, Springer-Verlag, 1982.
- [5] Juriev D., Topics in hidden symmetries, E-print (LANL Electronic Archive on Theor. High Energy Phys.): *hep-th/9405050* (1994).
- [6] Dubrovin B.A., Krichever I.M., Novikov S.P., Current Problems of Math., Fundamental Directions. Vol.4. Moscow, VINITI, 1985, pp.179-284 [in Russian]; Thirring W., *Classical dynamical systems*, Springer-Verlag, 1978.
- [7] Juriev D., On the nonhamiltonian interaction of two rotators, E-print (MSRI Electronic Archive on Diff. Geom. and Global Anal.): *dg-ga/9409005* (1994).
- [8] Semenov-Tian-Shansky M.A., *Funct. Anal. Appl.* 17, 259 (1983), *Zap. Nauchn. Sem. LOMI* 133, 228 (1984).
- [9] Semenov-Tian-Shansky M.A., *Publ. RIMS* 21, 1237 (1985), *Zap. Nauchn. Sem. LOMI* 150, 119 (1986).
- [10] Fomenko A.T., Trofimov V.V., *Geometric and algebraic mechanisms of integrability of hamiltonian systems on homogeneous spaces and Lie algebras*. In "Current Probl. Math.: Fundamental Directions 16", 1987, pp.227-295.